



T100

2-Ch Amplifier



T100

This 2-channel class D power amplifier features a mono or stereo speaker output, with support for 4-ohm and 8-ohm speakers. It can deliver 100 watts per channel into 8-ohm loads or 150 watts per channel into 4-ohm loads. Stereo looping outputs allow you to loop amplifiers together to create additional audio zones. Budget-friendly and versatile, it is compatible with dual voltage 110V/220V, can be programmed to work with any TV or control system and you can easily add bass with the sub-out. IR remote and wall-mount brackets are included. Optional AMP-CAN allows amp to easily disappear behind the TV.





Amplifier Type:
Channels:
Power Output, Continuous:
Bridged Power Output:
Power Requirements:
Impedance:
Inputs:
Outputs:
Control:
Dimensions:
Weight:
Certifications:

T100

Class D
 2 Channels
 100 Watts / Ch @ 8Ω
 150 Watts / Ch @ 4Ω
 275 Watts / Ch @ 8Ω
 120V - 240V @ 50 Hz - 60 Hz A/C
 4 - 8 Ω
 (1) Stereo RCA, (1) ToS
 (1) 3.5mm, (1) Subwoofer (with option of
 70Hz crossover or full range)
 (1) 3.5mm IR with built in learning. IR
 receiver also included

Family:

